

# Model 270 SETRACERAM<sup>™</sup> for Barometric, Gauge or Absolute Pressure

The Model 270 is Setra's highest performing analog sensor for barometric, absolute and gauge pressure measurements. Its decades worth of installations have built a reputation of reliability and remains the trusted choice for critical installations. The ceramic sensor on the 270 delivers high performance; its  $\pm 0.03\%$  FS accuracy over a wide temperature range outperforms competitive transducers in the environmental sensing market. The 270 offers multiple options to fit the needs of difficult applications, making it easier to install and gather higher quality data for your project.

#### **High Accuracy For Demanding Applications**

The Model 270 pressure transducer is the most accurate analog sensor Setra manufactures. The available 0.03% FS accuracy is perfect for vital installations where precise measurements determine success or failure of the application.

#### Improved Performance With Ceramic Sensor

The 270 utilizes a variable capacitance sensor that is made using ceramic material fused together with glass and gold to form the SETRACERAM<sup>™</sup> pressure element. This stable material and design offers class leading thermal performance and low hysteresis, allowing integration into demanding installations. The ceramic sensor enables improved performance compared to other stainless steel sensors, enabling the 270 to give accurate measurements and better test results.

#### **Flexibility in Installation**

The 270 offers mechanical and electrical options that can be installed into existing applications. These options reduce engineering design time, allowing for earlier project completion.



- Highest Accuracy Analog Sensor
- Captures Dynamic Pressure Changes
- Robust For Severe Weather Detection

#### Model 270 Features:

- High Optional Accuracy: ±0.03% FS
- Stable Ceramic Sensor
- Repeatability Within 0.01% FS
- Excellent Long-Term Stability: 0.1% FS/YR
- Low Power Consumption
- Instant Warm-Up
- Fast Response Time


#### **Applications:**

- High Accuracy Barometric Pressure Measurement
- Weather and Environmental Data
- Data Buoys and Remote Weather Stations
- Engine Test Cells

## **Model 270** SETRACERAM<sup>™</sup> for Barometric, Gauge or Absolute Pressure




## **ORDERING INFORMATION**



If 1 option: Option Code + N
If 2 options: Option Code + Option Code

## DIMENSIONS



Type of Pressure	Pressure Range	Maximum Pressure
Barometric	600 to 1100 hPa/mb 800 to 1100 hPa/mb	20 psia
Absolute	0 to 10, 20, 50, 100 psia	1.5 x rated
Gauge	0 to 5, 10, 20, 50, 100 psig	1.5 x rated

Performance Data		Environmental Data	
Accuracy RSS <sup>1</sup> (at constant temp)	±0.05% FS	Temperature	
Non-Linearity		Operating °F(°C)	0 to +175 (-18 to +80)
End Point	±0.05% FS	Storage °F(°C)	-65 to +250 (-54 to +120)
Best Fit Straight Line	±0.03% FS	Vibration	2g from 5Hz to 500 Hz
Hysteresis	<0.01% FS (TYP.)	Acceleration	10g
Resolution	Infinite, limited only by output noise level (0.005% FS)	Shock	50g Operating, 1/2 sine 10ms
Thermal Effects <sup>2</sup>		Pressure Fitting	1/8"-27 NPT Internal
Compensated Range °F(°C)	+30 to +120 (-1 to +49)	Electrical Connection	2' Multiconductor Cable
Thermal Zero Shift %FS/°100F (%FS/50°C)		Weight (approx.)	9 ounces (0.25 Kgm)
Barometric	±0.2 (±0.18)	Electrical Data	
Other Ranges	±0.1 (±0.09)	Electrical Circuit <sup>3</sup>	4-Wire (+Exc, -Exc, _Out, -Out)
Thermal Coefficient Sensitivity	±0.1 (±0.09)	Excitation <sup>4</sup>	24 VDC (22-32 VDC) 12VDC (11-15 VDC) Reverse Wiring Protection
Long Term Stability	< ±0.1% FS/YR		
Warm-Up	$<\pm$ 0.04% FS shift after 20 minutes at constant temp.	Output <sup>s</sup>	O to 5 VDC <sup>6</sup>
Time Constant	<10 milliseconds to reach 90% final output with step function pressure input	Isolation	The insulation resistance between all signals leads tied together and case ground is 100 ohms minimum at 25 VDC
Pressure Media		Output Impedance	<5 ohms
Non-condensing air or gas compatible with hard anodized aluminum, alumina ceramics, gold, fluorocarbon elastomer sealant & Buna-N O-Ring.		Output Noise	<200 microvolts RMS (0 Hz to 100 Hz)
		Current Consumption	8 mA (0.2 Watts)
Approvals			
CE			

## **GENERAL SPECIFICATIONS**